

APPENDIX A.
LIST OF MAIN COMPONENTS.

Reception Set R.206 MK. I.

<i>Component.</i>	<i>Symbol.</i>	<i>Value.</i>	
Condensers.	C1A-D	Gang variable	
	C2A	10 pF	
	C3A-D	10 pF	
	C4A-N	25 pF	
	C5A-L	50 pF	
	C6A	0.5 pF	
	C7A-C	140 pF	
	C8A	150 pF	
	C9A	3000 pF	
	C10A	2580 pF	
	C11A	1150 pF	
	C12A	610 pF	
	C13A	360 pF	
	C14A-B	200 pF	
	C15A-T	0.01 uF	
	C16A	50 pF	
	C17A-C	50 pF	
	C18A	350 pF	
	C19A-E	400 pF	
	C20A	425 pF	
	C21A-S	0.1 uF	
	C22A	20 pF	
	C23A-B	100 pF	
	C24A	500 pF	
	C25A	0.1 uF	
	C26A-B	1000 pF	
	C27A	0.01 uF	
	C28A-B	0.02 uF	
	C29A	10 pF	
	C30A-B	25 uF	
	C31A	100 pF	
	C32A	50 pF	
	C33A-E	0.05 uF	
	Resistors	R1A-D	5K ohms
		R2A-M	1K ohms
R3A-E		500 ohms	
R4A-B		300 ohms	
R5A-D		400 ohms	
R6A-F		0.25 Megohms	
R7A		100 ohms	
R8A-B		75K ohms	
R9A		4K ohms	
R10A-B		30K ohms	
R11A-F		50K ohms	
R12A-B		30K ohms	
R13A-D		100K ohms	
R14A-D		10K ohms	
R15A-B		0.5 Megohms	
R16A		20K ohms	
R17A		200K ohms	
R18A		1 Megohm	
R19A		10K ohms	
R21A		1 Megohm	
R22A		2K ohms	
R23A		30 ohms wire wound on 1000 ohms.	